


**PNP Transistors**



**Features**

- Complementary to MMBT3904
- Marking: 2A

**Absolute Maximum Ratings (Ta=25°C)**

Parameter	Symbol	Rating	Unit
Collector - Base Voltage	V <sub>CB0</sub>	-40	V
Collector - Emitter Voltage	V <sub>CE0</sub>	-40	
Emitter - Base Voltage	V <sub>EB0</sub>	-5	
Collector Current - Continuous	I <sub>c</sub>	-0.2	A
Collector Power Dissipation	P <sub>c</sub>	0.2	W
Junction Temperature	T <sub>J</sub>	150	°C
Storage Temperature range	T <sub>stg</sub>	-55 to 150	









**Electrical Characteristics (Ta=25°C unless otherwise specified.)**

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Collector- base breakdown voltage	V <sub>CB0</sub>	I <sub>c</sub> = -100 μA, I <sub>E</sub> =0	-40			V
Collector- emitter breakdown voltage	V <sub>CE0</sub>	I <sub>c</sub> = -1 mA, I <sub>B</sub> =0	-40			
Emitter - base breakdown voltage	V <sub>EB0</sub>	I <sub>E</sub> = -100 μA, I <sub>c</sub> =0	-6			
Collector-base cut-off current	I <sub>CB0</sub>	V <sub>CB</sub> = -40 V, I <sub>E</sub> =0			-100	nA
Collector- emitter cut-off current	I <sub>CEX</sub>	V <sub>CE</sub> = -30 V, V <sub>EB(off)</sub> =3V			-50	
Emitter cut-off current	I <sub>EB0</sub>	V <sub>EB</sub> = -5V, I <sub>c</sub> =0			-100	
Collector-emitter saturation voltage	V <sub>CE(sat)</sub>	I <sub>c</sub> =-10 mA, I <sub>B</sub> =-1mA			-0.2	V
		I <sub>c</sub> =-50 mA, I <sub>B</sub> =-5mA			-0.3	
Base - emitter saturation voltage	V <sub>BE(sat)</sub>	I <sub>c</sub> = -10 mA, I <sub>B</sub> = -1mA	-0.65		-0.85	
		I <sub>c</sub> = -50 mA, I <sub>B</sub> = -5mA			-0.95	
DC current gain	h <sub>fe</sub> (1)	V <sub>CE</sub> = -1V, I <sub>c</sub> = -10mA	100		300	
	h <sub>fe</sub> (2)	V <sub>CE</sub> = -1V, I <sub>c</sub> =-50mA	60			
	h <sub>fe</sub> (3)	V <sub>CE</sub> = -1V, I <sub>c</sub> =-100mA	30			
Delay time	t <sub>d</sub>	V <sub>CC</sub> =-3.0V, V <sub>BE</sub> =0.5V			35	ns
Rise time	t <sub>r</sub>	I <sub>c</sub> =-10mA, I <sub>B1</sub> =-1.0mA			35	
Storage time	t <sub>s</sub>	V <sub>CC</sub> =-3.0V, I <sub>c</sub> =-10mA			225	
Fall time	t <sub>f</sub>	I <sub>B1</sub> =I <sub>B2</sub> =-1.0mA			75	
Collector input capacitance	C <sub>ib</sub>	V <sub>EB</sub> = -0.5V, I <sub>E</sub> = 0, f=1MHz			10	pF
Collector output capacitance	C <sub>ob</sub>	V <sub>CB</sub> = -5V, I <sub>E</sub> = 0, f=1MHz			4.5	
Transition frequency	f <sub>T</sub>	V <sub>CE</sub> = -20V, I <sub>c</sub> = -10mA, f=100MHz	250			MHz

**hFE Classification**

Type	MMBT3906	MMBT3906-L	MMBT3906-H
Range	100-300	100-200	200-300

**Typical Characteristics**



**Ordering information**


Package	Packing Description	Base Quantity	Packing Quantity
SOT-23	Tape/Reel,7"reel	3000pcs/Reel	24000PCS/Box 120000PCS/Carton

**Package Dimensions**

**SOT-23**

Dim.	Millimeter (mm)		mil	
	Min.	Max.	Min.	Max.
A	0.9	1.15	35	45
A1	0.1		3.9	
bp	0.38	0.48	15	19
C	0.09	0.15	3.54	5.9
D	2.8	3.0	110	118
E	1.2	1.4	47	55
E	1.9		75	
E1	0.95		37	
HE	2.1	2.55	83	100
Lp	0.15	0.45	5.9	18
Q	0.45	0.55	18	22
v	0.2		7.9	
W	0.1		4	

**The recommended mounting pad size**



## Disclaimer

The information presented in this document is for reference only. GuangDong Youfeng Microelectronics Co.,Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise. The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), YFW or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale. This publication supersedes & replaces all information previously supplied. For additional information, please visit our website <https://www.yfwdiode.com>, or consult YFW sales office for further assistance.